

Parking Lot Sensor | PLS

Wireless sensors for detecting parking space occupancy

Wireless sensors detect and report parking space occupancy, thus enabling active parking lot management features, such as search, navigation and reservation.

The easy retrofit solution for parking lots is installed in minutes. It was designed for detecting with high reliability if a parking space is occupied or available.



OPERATING CONDITIONS

TARGET MARKETS AND CERTIFICATIONS

Reference	Range	PLS Variant	
Operating temperature range	- 20 + 65 °C	TPS110 EU	European Union (CE)
Humidity range	095 %		Singapore (IMDA)
Resistant to mechanical influences ² : snow-plough ³ , heavy		TPS110 JP	Japan (MIC)
goods vehicles (CV) (N1 - N3) 4 and high-pressure			Australia (ACMA) Singapore (IMDA)
cleaning		TPS110 IN	India (WPC/ETA)

COMMUNICATION

PLS Variant	LoRa Frequencies	Transmitting Power	
TPS110 EU	863-865/868-868.6/869.4-869.65 MHz (EU868)	max. 14 dBm ERP	
Supported channel frequencies: 864.1 MHz, 864.3 MHz, 864.5 MHz, 868.1 MHz, 868.3 MHz, 868.5 MHz, 869.525 MHz			
TPS110 JP	920-923.4 MHz (AS923)	max. 14 dBm ERP	
TPS110 IN	865-867 MHz (IN865)	max. 14 dBm ERP	
Radar frequency: 2.4-2.4835 GHz; transmission power max28 dBm EIRP			

1 The actual colour tone may differ from that shown on the data sheet. The exact colour designations can be found on page two

2 According to product specifications 3 Max. weight of 5,5 tons, shield: flexible flap towards ground, weight max. 1 ton, max. speed 20 km/h

4 Definition of Commercial Vehicles Categories: 2007/46/EC as last amended by 385/2009 and mechanical influences on the parking lot sensor only through the tires of the vehicles.

DEVICE SPECIFICATION



	Reference	Specification	0
	Weight	191 g	
	Power supply	Lithium battery (Li-SOCI2, 3.6V, 1200mAh)	
	Battery lifetime	Up to 5 years ⁷	
	IP class	IP67/IPx9K	
Installation and Maintenance		nd Maintenance	
	Installation	Sensor to glue to different surfaces / screw in the ground ⁵	
	Maintenance	No maintenance needed	

Replacement Core exchangeable without removing the base from the ground

Performance Parameters

- Model based optimized parking state detection algorithm development with millions of data points from real parking events, adaptive algorithm ensure high detection reliability during the whole sensor lifetime
- 96% average parking state change detection performance⁷ proven in field-tests with more than 2000 sensors and more ► than 46 different car types in real parking environments
- Self-learning calibration during the first five parking events ►
- Reporting of parking state changes within 35 sec. (typical) ►

COMPONENTS

Cover Cap	
Color	RAL9005 / black
Weight	2 g
Material	PA6 GF35
Description	The cap with O-ring is positioned on top of the sensor
	core to protect the screw.
Sensor Core ((TPS110)
Color	RAL9005 / black; RAL7011 / irongrey
Weight	124 g
Material	PA6 GF35
Description	The Sensor-Core contains the sensing unit. It consists
	of housing, integrated battery, electronics, o-rings.
	The core will be installed into the base.
Sensor Base	
Color	Standard: RAL7011 (irongrey); further colours: RAL030.50.60
	(Bosch red); RAL250, 60, 40 (D2) (Bosch Light Blue); RAL1023
	(Traffic Yellow); RAL120.70.75 (D2) (Bosch Light Green) ⁶
Weight	65 g
Material	PA6 GF35 (plasma treated on the bottom side)
Description	The Sensor Base is the part that is mounted on the ground.

PARKING LOT SENSOR - INSTALLED STATE

5 Requires separate 2K PUR based adhesive or screws anchor belts and sealing 6 Standard: RAL7011, other colours on request

7 Detailed conditions of the performance information are inside of the offer documentation

GET IN CONTACT WITH US!

E-Mail: support@bosch-connectivity.com

Website: www.bosch-connectivity.com/parking-lot-sensor

Technical data subject to modification without notice.

© Bosch Connected Devices and Solutions GmbH 2020. All rights reserved, also uction, editing, distribution, as well as in the event of application for industrial property rights. December 04, 2020

DRAWING / DIMENSIONS



